



Competence in
Communication
Technologies

SES 5216-06

Single cable multiswitch II (SCR) | 5 in 2 × 16

SES 5216-06, SES 5416-06 and SES 5816-06 have 2/4/8 two subscriber outputs. 16 user bands are available on each of these.


- All 16 user bands can be used for receivers, which comply with EN 50607.
- Eight user bands can be used for receivers, which comply with EN 50494.

User bands standard programming*

User bands	Frequency [MHz]	Suitable for receivers compliant to EN 50494	Suitable for receivers compliant to EN 50607
UB1	975	yes	yes
UB2	1025	yes	yes
UB3	1075	yes	yes
UB4	1125	yes	yes
UB5	1175	yes	yes
UB6	1225	yes	yes
UB7	1275	yes	yes
UB8	1325	yes	yes
UB9	1375	no	yes
UB10	1425	no	yes
UB11	1475	no	yes
UB12	1525	no	yes
UB13	1575	no	yes
UB14	1625	no	yes
UB15	1675	no	yes
UB16	1725	no	yes

Notes:

- Wideband LNB: The AXING single cable multi-switches can be used with a wideband LNB with an oscillator frequency of 10.4 GHz
- The legacy mode cannot be used with programmable antenna sockets SSD 6-xx!
- The legacy mode cannot be used with wideband LNBs!
- *A customer-specific user band allocation is possible.



AXING AG
Gewerbehaus Moskau
Telefon +41 52 - 742 83 00
Telefax +41 52 - 742 83 19

CH-8262 Ramsen
info@axing.com
www.axing.com