




# Kanalbelegung Breitbandkabel


## Digitale Kabelkanäle in Deutschland

Frequenz / MHz	Kanal	Kanal (klass.)	Bandbreite
114,00	D114		8 MHz
122,00	D122		8 MHz
130,00	D130		8 MHz
138,00	D138		8 MHz
146,00	D146		8 MHz
154,00	D154		8 MHz
162,00	D162		8 MHz
170,00	D170		8 MHz
178,00	D178		8 MHz
186,00	D186		8 MHz
194,00	D194		8 MHz
202,00	D202		8 MHz
210,00	D210		8 MHz
218,00	D218		8 MHz
226,00	D226		8 MHz
234,00	D234		8 MHz
242,00	D242		8 MHz
250,00	D250		8 MHz
258,00	D258		8 MHz
266,00	D266		8 MHz
274,00	D274		8 MHz
282,00	D282		8 MHz
290,00	D290		8 MHz
298,00	D298		8 MHz
306,00	D306	S21	8 MHz
314,00	D314	S22	8 MHz
322,00	D322	S23	8 MHz
330,00	D330	S24	8 MHz
338,00	D338	S25	8 MHz
346,00	D346	S26	8 MHz
354,00	D354	S27	8 MHz
362,00	D362	S28	8 MHz
370,00	D370	S29	8 MHz
378,00	D378	S30	8 MHz
386,00	D386	S31	8 MHz
394,00	D394	S32	8 MHz
402,00	D402	S33	8 MHz
410,00	D410	S34	8 MHz
418,00	D418	S35	8 MHz
426,00	D426	S36	8 MHz
434,00	D434	S37	8 MHz





442,00	D442	S38	8 MHz
450,00	D450	S39	8 MHz
458,00	D458	S40	8 MHz
466,00	D466	S41	8 MHz
474,00	D474	E21	8 MHz
482,00	D482	E22	8 MHz
490,00	D490	E23	8 MHz
498,00	D498	E24	8 MHz
506,00	D506	E25	8 MHz
514,00	D514	E26	8 MHz
522,00	D522	E27	8 MHz
530,00	D530	E28	8 MHz
538,00	D538	E29	8 MHz
546,00	D546	E30	8 MHz
554,00	D554	E31	8 MHz
562,00	D562	E32	8 MHz
570,00	D570	E33	8 MHz
578,00	D578	E34	8 MHz
586,00	D586	E35	8 MHz
594,00	D594	E36	8 MHz
602,00	D602	E37	8 MHz
610,00	D610	E38	8 MHz
618,00	D618	E39	8 MHz
626,00	D626	E40	8 MHz
634,00	D634	E41	8 MHz
642,00	D642	E42	8 MHz
650,00	D650	E43	8 MHz
658,00	D658	E44	8 MHz
666,00	D666	E45	8 MHz
674,00	D674	E46	8 MHz
682,00	D682	E47	8 MHz
690,00	D690	E48	8 MHz
698,00	D698	E49	8 MHz
706,00	D706	E50	8 MHz
714,00	D714	E51	8 MHz
722,00	D722	E52	8 MHz
730,00	D730	E53	8 MHz
738,00	D738	E54	8 MHz
746,00	D746	E55	8 MHz
754,00	D754	E56	8 MHz
762,00	D762	E57	8 MHz
770,00	D770	E58	8 MHz
778,00	D778	E59	8 MHz
786,00	D786	E60	8 MHz
794,00	D794	E61	8 MHz
802,00	D802	E62	8 MHz
810,00	D810	E63	8 MHz



AXING AG

Gewerbehau Moskau

Telefon +41 52 - 742 83 00

Telefax +41 52 - 742 83 19


CH-8262 Ramsen

info@axing.com

www.axing.com



818,00	D818	E64	8 MHz
826,00	D826	E65	8 MHz
834,00	D834	E66	8 MHz
842,00	D842	E67	8 MHz
850,00	D850	E68	8 MHz
858,00	D858	E69	8 MHz
866,00	D866		8 MHz
874,00	D874		8 MHz
882,00	D882		8 MHz
890,00	D890		8 MHz
898,00	D898		8 MHz
906,00	D906		8 MHz
914,00	D914		8 MHz
922,00	D922		8 MHz
930,00	D930		8 MHz
938,00	D938		8 MHz
946,00	D946		8 MHz
954,00	D954		8 MHz
962,00	D962		8 MHz
970,00	D970		8 MHz
978,00	D978		8 MHz
986,00	D986		8 MHz
994,00	D994		8 MHz
1002,00	D1002		8 MHz



AXING AG

Gewerbehaus Moskau

Telefon +41 52 - 742 83 00

Telefax +41 52 - 742 83 19

CH-8262 Ramsen

info@axing.com

www.axing.com