



DEF


Definitions:

Level and power measures	
dB μ V	Voltage level in relation to 1 μ V (Interpretation: "by how many dB is a voltage higher than 1 μ V")
dBmV	Voltage level in relation to 1 mV (Interpretation: "by how many dB is a voltage higher than 1 mV")
dBm	Power level in relation to 1 mW (Interpretation: "by how many dB is a power higher than 1 mW")

Converting formulas
$dB\mu V = dBmV + 60 \text{ dB}$
$dBmV = dB\mu V - 60 \text{ dB}$
$dB\mu V = dBm + 108.75 \text{ dB (with } Z = 75 \Omega)$
$dB\mu V = dBm + 107.00 \text{ dB (with } Z = 50 \Omega)$

Frequency bands	
HF: High Frequency	3 MHz ... 30 MHz
VHF: Very High Frequency	30 MHz ... 300 MHz
UHF Ultra High Frequency	300 MHz ... 3 GHz

Level relations in a broadband cable network	
System level (traditionally)	PAL image carrier level
DVB-C / DOCSIS ≤ 3.0 @ 64 QAM	PAL - 10 dB
DVB-C / DOCSIS ≤ 3.0 @ 256 QAM	PAL - 4 dB



AXING AG

Gewerbehaus Moskau

Telefon +41 52 - 742 83 00

Telefax +41 52 - 742 83 19

CH-8262 Ramsen

info@axing.com

www.axing.com