# BSD 4-00N CATV end outlet 5…1006 MHz




- ✔ Suitable for broadband return path
- ✔ Surface treated

## Order information

| | |
|---|---|
| **Type** | BSD 4-00N |
| **Order no.** | BSD00400N |
| **GTIN** | 7611682007305 |
| **PE** | 1 |
| **VE** | 1 |
| **EU customs tariff number** | 85291095 |

## Technical data

| | |
|---|---|
| **Tap method** | Ferrite splitter |
| **Trunk line** | |
| **Frequency range input** | 5…1006 MHz |
| **Isolation internal** | > 15 dB |
| **Frequency range output** | 5…1006 MHz |
| **Suitable cables (Inner conductor \| outer diameter)** | 0.63…1.13 mm \| 4.7…7.35 mm |
| **TV connector** | |
| **Connector type** | IEC-male |
| **Frequency range** | 5…1006 MHz |
| **Tap loss** | 4 dB ±2 dB |
| **Radio connector** | |
| **Connector type** | IEC-female |
| **Frequency range** | 5…1006 MHz |
| **Tap loss** | 4 dB ±2 dB |
| **General** | |
| **Dimensions (W × H × D) appr.** | 70 × 66 × 32 mm |
| **Weight** | 0.091 kg |

## Suitable products

TZU 2-00 Cover plate | TV/R | single piece
TZU 1-00 Surface frame
TZU 2-10 Cover plate | TV/R | two-parts
TZU 1-10 Surface frame