

## TZU 19-65 High-pass filter | return path blocker | 5...65 MHz



- ✓ Frequency range 85...862 MHz
- ✓ Frequency range blocked 5...68 MHz
- ✓ Vodafone listed

### Order information

|                          |               |
|--------------------------|---------------|
| Type                     | TZU 19-65     |
| Order no.                | TZU01965      |
| GTIN                     | 7611682081961 |
| PE                       | 1             |
| VE                       | 1             |
| EU customs tariff number | 85291080      |



### Technical data

|                                     |                         |
|-------------------------------------|-------------------------|
| Frequency range                     | 85...862 MHz            |
| Frequency range blocked             | 5...65 MHz              |
| Screening factor acc. to EN 50083-2 | > 90 dB                 |
| Blocking depth                      | > 50 dB                 |
| Through loss                        | 1.5...0.5 dB            |
| Connectors                          |                         |
| Connector type                      | F-female/F-male         |
| Return loss                         | > 18 dB...1.5 dB/Oktave |
| General                             |                         |
| Weight                              | 0.021 kg                |

### Suitable products

[EOC 1-31 Ethernet over Coax | Peer-to-Peer | 720 Mbps](#)  
[EOC 2-31 Ethernet over Coax | Peer-to-Peer | 720 Mbps | WiFi](#)  
[EOC 20-01 Ethernet over Coax | Master | 720 Mbps](#)  
[EOC 20-02 Ethernet over Coax | Endpoint | 720 Mbps](#)